

## Configuring Microstation V8 XM for Power Office 2005 on Vista

- Before any of the following software can be installed on Vista the Administrator rights must be changed as follows: ( using your mouse )
  - Left click on the Windows Start icon.
  - Left click on *Control Panel* then double left click on *User Account*.
  - Left click on Turn User Account Control On or Off.
  - Left click on 'User Account Control (UAC) to help protect you Computer check box to remove tick.
  - Click OK, You will then be asked to Restart you machine.
- Make sure that computer's files and folders are not hidden and the full path is displayed in the title bar. Change this by:
  - Left click on the *Windows Start* icon.
  - Left click on *Control Panel* then double left click on *Folder Options*. Left click on *View* tab and place a tick in the 'Display the full path in the title bar (Classic folders Only)' checkbox and then left click on '*Show hidden file and folders*' so that there is a dot in the radio button.
  - Left click on *Apply*
  - Left click *Ok* and close *Control Panel*.
- To configure Microstation V8 XM for PowerOffice. The User needs to define the path for the Cell library, Line Styles, Macros, Design Seed file and Toolbar File. This is explained below.

### **Cell Library**

- Open Microstation and left click on *Workspace* left click on *Configuration*.
- In the *Configuration: User [Untitled]* window, search and select *MS\_CellList* in the *View/Modify all configuration variables* window.
- Left click *Edit*.
- In the *Edit Configuration Variable* window, left click in the *Edit* select box and left click on *Prepend*.
- Right click on the *Windows Start* icon
- Left click on *Explore*.
- In the Folders window double left click on *Local Disk C:*.
- Double left click on the *Program Files* folder.
- Double click on the *Inspired Interfaces* folder.
- Double left click on the *PowerOffice* folder.
- Double left click on the *System Files* folder.
- In the address bar highlight the path. Right click and copy the path.
- Return to the Microstation *Edit Configuration Variable* Window, left click in the *New Value* block and right click and paste the path.
- Now type '*\*.cel* '.
- The path should read ' *C:\Program Files \Inspired Interfaces \Power Office \System Files \\*.cel* '
- Select *OK*

## Line Styles

- In the *Configuration: User [Untitled]* window, search and select *MS\_Symbrsrc* in the *View/Modify all configuration variables* window.
- Left click *Edit*.
- In the *Edit Configuration Variable* window, left click in the *Edit Mode* select box
- Left click on *Prepend*.
- In Configuration Window, left click in the *New Value* block and right click to paste the path.
- Type '*\\*.rsc*'
- The path should read '*C:\Program Files \InspiredInterfaces\ PowerOffice\ SystemFiles\\*.rsc*'
- Select *OK*

## Macros

- In the *Configuration: User* window search and select *MS\_Macro*.
- Left click on *edit*.
- In the *Edit Configuration Variable* window, left click in the *Edit Mode* select box and left click on *Prepend*.
- Open Windows *Explore*.
- In the Folders window double left click on *Local Disk C:*.
- Double left click on the *Program Files* folder.
- Double click on the *Inspired Interfaces* folder.
- Double left click on the *PowerOffice* folder.
- Left click on the *Macros V8XM* folder.
- In the address bar highlight the path. Right click and copy the path.
- Return to the Microstation *Edit Configuration Variable* Window, left click in the *New Value* block and right click and paste the path.
- Return to the Microstation Configuration Window, left click in the *New Value* block and paste.
- Type '*\*'
- The path should read '*C:\Program Files \Inspired Interfaces \PowerOffice \MacrosV8XM\*'
- Select *OK*

## Design Seed File

- In *Workspace* Configuration search and select *MS\_Designseed* and edit. In the *Edit Configuration Variable* window select *Overwrite*. Remove *design2d.dgn* and replace it with *Electrificationdesign.dgn*
- Left click *OK*
- Left click *OK* in the Configuration window.
- Select *YES* to save changes
- Open Windows *Explore*.
- In the Folders window double left click on *Local Disk C:*.
- Double left click on the *Program Files* folder.
- Double click on the *Inspired Interfaces* folder.
- Double left click on the *PowerOffice* folder.
- Left click on the *Support* file and select and copy the *ElectrificationDesign.dgn* file.
- Back in *Windows Explorer*, *C:\ProgramData\Bentley\Workspace\System\Seed* and paste *ElectrificationDesign.Dgn*

## Toolbar File

- Right click on the *Windows Start* icon
- Left click on *Explore*.
- In the Folders window double left click on *Local Disk C:*.
- Double left click on the *Program Files* folder.
- Double left click on the *Inspired Interfaces* folder.
- Double left click on the *Power Office* folder.
- Double left click on the *System Files* folder.
- Left click on *Toolbar V8* folder.
- Left click on ' *ustn.m01* ' file.
- Right click copy.
- In your *Windows Explore, Local Disk C:, Program Files* search for the *Program Data* folder.
- Double left click on the *Program Data* file.
- Double left click on the *Bentley* file.
- Double left click on the *Microstation* file.
- *Windows Explore* can now be closed.
  
- To view the Tool bar in Microstation select *Tools\Tool Boxes*. Scroll down to PO Electrification and tick all relevant boxes for PO Electrification
- Select *OK*